

## Upgrade and Configuration Utility Quick Start Guide

The *Upgrade and Configuration Utility* is to upgrade firmware and/or configure multiple CyberPower RMCARDS and monitored/switched PDUs at once. Logs are maintained in the utility for record keeping.

### Prerequisites

#### Hardware Requirements

- 133 MHz or higher Pentium-compatible processor
- Minimum 32 MB of RAM recommended
- Minimum 10 MB of free Hard Disk Drive space

#### Operating System

For 32 bit and 64 bit systems:

- Microsoft® Windows 10, 8, 7, Vista, and XP
- Microsoft® Windows Server 2012, 2008, and 2003

### Upgrade Firmware and/or Upload Configuration

1. Follow the setup wizard to install the software
2. Start the program by selecting it from Start>All Programs>CyberPower Upgrade and Configuration Utility.

#### Firmware Upgrade

1. Select Add from the Devices menu on the right. Type in the IP address, Account username and password for the device (RMCARD or PDU).
2. The device will be added to the device list. Select the device by selecting the checkbox next to it.
3. Select Upgrade Firmware from the Action menu.
4. Select the folder file path where the Firmware and Data files are located. Click OK to start the update process.

#### Upload Configuration

1. Select Add from the Devices menu on the right. Type in the IP address, Account username and password for the device (RMCARD or PDU).
2. The device will be added to the device list. Select the device by selecting the checkbox next to it.
3. Select Upload Configuration from the Action menu.
4. Select the folder file path where the Configuration file is located. Click OK to start the update process.

#### Notes

- Prior to uploading a configuration file to any device it must first be downloaded from the master/example device whose configuration will be replicated.
- Depending on firewall settings you may see an alert message preventing or blocking the *Upgrade and Configuration Utility* from operating. You will need to Unblock it in your firewall settings for it to operate.