

OfficePower™ 1000AVR

Automatic Voltage Regulator



1500
Joules

38 - 80
Minutes of
system runtime

CyberPower gives you lightning protection plus battery back-up with an automatic voltage regulator.

Includes software that saves open files and shuts off the computer automatically when power is interrupted.

AVR
AUTOMATIC VOLTAGE REGULATOR

PRODUCT FEATURES:

- Battery Run-times from 38 to 80 minutes
- Automatic Voltage Regulation Controls over-voltages, blackouts and brownouts
- USB & Serial Interface Compatibility
- Dual 7.2AH batteries for longer run-time
- All outlets are surge-protected at 1500 joules
- PowerPanel Plus™ Software included
- Internet-ready: 2 line phone, fax, modem surge protection
- \$350,000 Connected Equipment Warranty



Includes
PowerPanel Plus™
Intelligent Power Management Software
(Windows 98, ME, NT, 2000 & XP compatible)



- Saves open files, closes applications and shuts down your computer when a power outage occurs.
- Monitors input voltage, output voltage, battery capacity, load and unit temperature.
- Allows for user-defined scheduled shutdown and startup of computer system.

OfficePower™ 1000AVR

Automatic Voltage Regulator

High Performance Power Protection with Automatic Voltage Regulation

Brownouts are an everyday occurrence!

CyberPower's OfficePower™ 1000AVR Battery Back-up System with Automatic Voltage Regulator increases low or decreases high voltages to a consistent and computer safe 110/120 volts. The OfficePower™ 1000AVR not only guards against surges and spikes, but will also provide battery back-up power if line voltage drops below 85 volts or exceeds 150 volts.

In the event of a power outage, PowerPanel Plus™ Software automatically logs and saves all open files then shuts down the computer system in an intelligent and orderly manner.



Automatic Voltage Regulators increase low or decrease high voltage to a consistent and computer-safe 110/120 volts. The CPS1000AVR automatically provides battery backup power if the incoming line voltage drops below 85 volts or exceeds 150 volts.



- 1 - Battery Power / Surge Outlets
- 2 - Full-Time Surge Protection Outlets
- 3 - Power Switch
- 4 - Power On Indicator
- 5 - Wiring Fault Indicator
- 6 - Automatic Voltage Regulator
- 7 - Using Battery Indicator
- 8 - Check Battery Indicator
- 9 - Resettable Circuit Breaker
- 10 - Serial Port to PC
- 11 - Two (2) Line Phone/Fax/Modem Communication Protection Ports

TECHNICAL SPECIFICATIONS

Model	CPS1000AVR
VA Rating	1000VA
Watts	500W
Input Voltage on Utility	85V to 150V
Frequency on Utility	57Hz to 63 Hz
Output Voltage on Battery	120V +/- 5%
Frequency on Battery	60Hz
Surge Energy Capacity	1500 Joules
Maximum Surge Current	36,000 Amps
Overload Protection	Internal circuitry limiting. On-line circuit breaker
Battery Run-time	38 to 80 minutes
Typical Battery Recharge Time	8 hours
Total number of receptacles	3 battery / surge, 3 full-time surge-only
Visual Indicators	Power On/Off, Automatic Voltage Regulator, Using Battery, Site Wiring Fault
Audible Indicators	Battery on, Low battery, UPS overload
Warranty	Three Year Limited Warranty on UPS unit and battery
Conformance Approvals	UL 1778, cUL, FCC Doc Class B
Included Software	PowerPanelPlus™ Power Management Software
Connected Equipment Guarantee	\$350,000

(Sample Packaging)



ORDERING INFORMATION

Part Number	CPS1000AVR
Sell Unit Dims. (L" x W" x H")	14.5" x 9.25" x 8"
Sell Unit Net Weight	29 LBS.
Master Carton Quantity	2 UNITS
Master Dims. (L" x W" x H")	15.25" x 16.75" x 10"
Master Weight	57 LBS.
UPC Number	6 49532 21000 8

CyberPower™

5555 12th Avenue East, Suite 110, Shakopee, MN 55379
Phone: 877.297.6937 Fax: 952.403.0009

For more information, visit CyberPower's Web Site at www.cyberpowersystems.com or call 1-877-CY-POWER