# **Cyber Power**



### **CPS100BU Mobile Power Inverter**

Offering household power on the go.

The CPS100BU Inverter converts 12v DC automobile power to standard 120v AC home power - up to 100 watts. Simply plug the inverter into a 12v DC outlet (cigarette lighter outlet) and you're ready to go. Its compact design and convenient 150-degree swivel head is designed to fit in all universal cigarette lighter receptacles. It is equipped with one 3-prong outlet and has built-in automatic shutdown to protect your vehicle's battery.

Full-time surge protection guards against power fluctuations from vehicle startup and shutdown. It's the perfect device to power all your mobile/consumer electronics, small appliances, emergency equipment, and portable tools. It also includes a USB port for changing your mobile electronics.

A Two-Year Warranty ensures that this product has passed our highest quality standards in design, assembly, material and workmanship.

#### **Typical Applications**

- Tablets
- Laptops
- Smartphones

#### Features

- 100W Power Inverter
- 150° Swivel Head
- (1) USB 1.0 Amp Charging Port
- (1) 120Vac Outlet
- Surge Protected
- 2-Year Warranty

## **CPS100BU Mobile Power Inverter**

Offering household power on the go.

GENERAL	
Product Type	Power Inverter
INPUT	
Voltage	10.5Vdc - 15.5Vdc
Current	10A max
Plug Type	12Vdc Auto Power Port
OUTPUT	
On Battery Voltage	120Vac
On Battery Frequency	60Hz
On Battery Waveform	Simulated Sine Wave
Outlet Type	NEMA 5-15R
Watts - Continuous	100
Watts - Peak	120
USB Charge	5Vdc @ 1A
CERTIFICATIONS	
Environmental	RoHS Compliant
WARRANTY	
Product Warranty	2 Years Limited