



CPS100PBU 100W AC POWER INVERTER WITH USB-A

Offering household power on the go

The AC Power Inverter model CPS100PBU from CyberPower converts your vehicle's DC power to household AC power to charge and operate devices which use 75 watts of power continuously, up to 100W of peak power (10 seconds maximum). It also provides one 2.4A USB-A port for mobile device charging, and automatic shutdown to safeguard your vehicle's battery from dropping below normal values necessary for start-up. A two-year limited warranty comes with the CPS100PBU. The 10 amp replaceable fuse provides protection for your devices from under/over voltage, short circuits, overloads, and over-charging.



TYPICAL APPLICATIONS

- Mobile Devices
- Tablets
- Portable DVD Players
- Digital Camera battery chargers

FEATURES

- 10.5 - 15.5V DC Input Voltage
- 12V DC Auto Power Port Plug
- 100W (peak), 75W (continuous) output
- NEMA 5-15R Outlet (1)
- 5V, 2.4A USB-A Charging Port (1)
- Automatic shutdown
- 2-Year Warranty

SPECIFICATIONS

INPUT	
Input Voltage Range	10.5 - 15.5V DC
Plug Type	12V DC Auto Power Port
OUTPUT	
AC Output Watts - Continuous	75
AC Watts - Peak	100
AC Outlet Type	NEMA 5-15R
AC Output Voltage	120V AC
AC Output Frequency	60Hz
AC Outlets	1
USB Ports	1 Type-A
USB Output	5V, 2.4A

ENVIRONMENTAL	
Operating Temperature	32 °F to 104 °F / 0 °C to 40 °C
Storage Temperature	32°F to 86°F / 0°C to 30°C
Maximum Storage Elevation	50,000 ft / 15,000 m
Operating Relative Humidity	0% - 95% non-condensing
Maximum Operating Elevation	10,000 ft / 3,000 m
CERTIFICATIONS	
Environmental	RoHS Compliant
WARRANTY	
Product Warranty	2 Years Limited