



RB1290X4J REPLACEMENT BATTERY



Restore life to UPS systems that have weak or depleted internal batteries

The RB1290X4J UPS Replacement Battery Cartridge restores life to CyberPower UPS systems that have weak or completely depleted internal batteries. The RB1290X4J contains four 12V/9Ah batteries, certified to meet or exceed original manufacturer specifications. This leak-proof, sealed lead-acid battery never requires replacement fluid. The pre-assembled cartridge installs easily into your CyberPower UPS system and is shipped with reusable packaging for delivering expired batteries to a suitable recycling center. The RB1290X4J comes with instructions, recycling information, and an eighteen-month warranty.

FEATURES

- Sealed Lead-Acid Battery
- Maintenance-Free Battery Fluid
- Leak-Proof Casing
- User-Installable Cartridge
- Reusable Packaging
- OEM Certified
- Eighteen-Month Warranty

SPECIFICATIONS

BATTERY	
Battery	4
Battery Size	12 V / 9 Ah
Battery Type	Sealed Lead-Acid Battery
User-Replaceable Battery	Yes
DIMENSIONS	
Physical Dimensions - WxHxD (cm)	20.83 x 6.6 x 31.5 cm
Physical Dimensions - WxHxD (mm)	208 x 66 x 315 mm
Physical Dimensions - WxHxD (in.)	8.2 x 2.6 x 12.4 in
Weight (kg)	10.89 kg
Weight (lb)	24.0 lbs.
SHIPPING DIMENSIONS	
Shipping Dimensions - WxHxD (cm)	36.58 x 16.51 x 48.01 cm
Shipping Dimensions - WxHxD (mm)	365.76 x 165.1 x 480.06 mm
Shipping Dimensions - WxHxD (in)	14.4 x 6.5 x 18.9 in.
Shipping Weight (kg)	11.88 kg
Shipping Weight (lbs.)	26.2 lbs.

CONTENTS	
Package Includes	Battery Kit and Installation Guide
ENVIRONMENTAL	
Operating Relative Humidity	0 - 90 % (non-condensing)
Operating Temperature	32 - 104 °F (0 - 40 °C)
COMPATIBILITY	
UPS Models	PR1500RT2U PR1500RTXL2U PR2000RT2U PR2000RTXL2U PR2200RT2U PR2200RTXL2U PR3000RT2U PR3000RTXL2U PR1500RT2UN PR1500RTXL2UN PR2000RT2UN PR2000RTXL2UN PR2200RT2UN PR2200RTXL2UN PR3000RT2UN PR3000RTXL2UN
WARRANTY	
Product Warranty	18-Month Limited Warranty