

OL6000RT3UTF RUNTIME



FEATURES

- 6,000VA / 5,400W Pure Sine Wave UPS
- Step-Down Transformer
- Output: 120V; 200-240V UPS
- GreenPower UPS™ ECO Power Mode
- SNMP Options for remote monitoring
- Generator compatibility mode
- 9 Outlets / USB, Serial, EPO, and Dry Contact Port
- 8U Rack Mount
- PowerPanel® Business Edition Software

RUNTIMES IN MINUTES

Model/Watts	500W	600W	700W	800W	900W	1000W	1100W	1200W	1300W	1400W	1500W	1600W	1700W	1800W	1900W
OL6000RT3U	74	62	53	47	42	38	35	33	31	29	27	27	27	26	25
OL6000RT3U +1BP	170	143	123	109	99	90	83	78	73	69	66	65	64	61	59
OL6000RT3U +2BP	295	241	205	178	161	147	136	127	119	113	107	105	103	99	95
OL6000RT3U +3BP	417	350	303	265	235	212	194	179	169	159	152	145	144	139	134
OL6000RT3U +4BP	544	456	396	351	317	289	264	244	227	213	201	191	189	181	175
OL6000RT3U +5BP	667	567	492	436	394	361	334	312	292	274	259	245	242	231	222
OL6000RT3U +6BP	787	673	591	524	474	434	401	375	352	333	317	303	297	285	274
OL6000RT3U +7BP	908	776	683	613	555	508	470	439	413	391	372	355	349	336	324
OL6000RT3U +8BP	1031	881	775	696	635	585	541	505	475	450	428	409	402	387	373
OL6000RT3U +9BP	1154	986	867	779	711	656	612	573	539	510	485	463	455	438	423
OL6000RT3U +10BP	1278	1092	961	863	787	727	678	637	603	571	543	519	510	491	474

RUNTIME IN MINUTES

Model/Watts	2200W	2300W	2400W	2500W	2600W	2700W	2800W	2900W	3000W	3100W	3200W	3300W	3400W	3500W	3600W	3700W
OL6000RT3U	21	20	19	18	17	15	14	14	13	12	12	11	11	10	10	10
OL6000RT3U +1BP	51	48	46	43	41	38	36	35	33	32	31	29	28	27	26	25
OL6000RT3U +2BP	83	78	74	71	68	62	60	57	55	53	51	49	47	45	44	42
OL6000RT3U +3BP	116	110	105	100	95	87	84	80	77	74	71	69	67	64	62	60
OL6000RT3U +4BP	151	143	136	130	124	114	109	105	100	97	93	90	87	84	81	78
OL6000RT3U +5BP	188	178	169	161	154	141	135	130	125	120	116	111	108	104	100	97
OL6000RT3U +6BP	232	218	206	195	185	169	162	156	150	144	139	134	129	125	121	117
OL6000RT3U +7BP	278	262	247	234	222	201	191	183	175	168	162	156	151	146	141	137
OL6000RT3U +8BP	322	306	289	274	260	236	224	214	204	196	187	180	174	168	162	157
OL6000RT3U +9BP	365	347	329	314	299	272	259	247	236	225	216	207	199	191	184	178
OL6000RT3U +10BP	409	388	335	308	294	280	268	256	246	236	226	218	210	202	195	188

OL6000RT3UTF RUNTIME CONT.



RUNTIME IN MINUTES																	
Model/Watts	3800W	3900W	4000W	4100W	4200W	4300W	4400W	4500W	4600W	4700W	4800W	4900W	5000W	5100W	5200W	5300W	5400W
OL6000RT3U	9	9	9	8	8	8	8	7	7	7	7	6	6	6	6	6	5
OL6000RT3U +1BP	24	24	23	22	22	21	21	20	20	19	19	18	18	17	17	16	16
OL6000RT3U +2BP	41	40	39	38	37	36	35	34	33	32	32	31	30	30	29	28	28
OL6000RT3U +3BP	58	56	55	54	52	52	50	49	47	46	45	44	43	42	41	40	39
OL6000RT3U +4BP	76	74	72	70	68	67	66	64	62	61	59	59	57	56	54	53	52
OL6000RT3U +5BP	94	91	90	87	85	84	81	79	77	75	73	73	71	69	68	66	65
OL6000RT3U +6BP	113	110	108	105	102	100	98	95	93	90	88	87	85	83	81	80	78
OL6000RT3U +7BP	132	128	126	123	119	118	114	111	109	106	103	102	100	97	95	93	91
OL6000RT3U +8BP	152	148	145	141	137	135	132	128	125	122	119	117	115	112	109	107	105
OL6000RT3U +9BP	172	167	165	160	155	153	149	145	141	138	134	133	130	127	124	121	119
OL6000RT3U +10BP	308	294	280	268	256	246	167	162	158	154	150	149	145	142	139	136	133